



Portable Power Station

Model: **AK-PS-02**



DC output voltage	2x 5.5x2.1 mm: 12 V / 3 A, 1x cigarette lighter connector: 12 V / 10 A
USB-A output voltage	2x USB-A: 5 V / 3 A, 9 V / 2 A, 12 V / 1.5 A (Max. 18 W)
USB-C output voltage	2x USB-C: 5 V / 5 A, 9 V / 5 A, 12 V / 5 A, 15 V / 5 A, 20 V / 5 A (Max. 100 W)
Product code	AK-PS-02
Product type	Portable Power Station
Total number of USB connectors	6 pcs
DC Output Voltage	5 - 20 V
AC Output Voltage	230 V / 50 Hz
Battery cycle life	1000 times, DOD>80%
Battery type	Li-ion 22.2 V
Maximum power	1200 W
OVP	Yes
OCP	Yes
OPP	Yes
OTP	Yes
SCP	Yes
UVP	Yes
Product color	Black
Display	Yes
Temperature	0°C - 40°C
Product size (L x W x H)	380 x 220 x 260 mm
Net weight	11.26 kg
CE compatibility	Yes
RoHS compatibility	Yes
Included accessories	AC/DC adapter, Power cable
EAN code	5901720137937
Warranty	24 months





Description

Akyga® AK-PS-02 portable power station is a useful device for all lovers of active outdoor activities. Whether we are camping or on a yacht, the power station is a safe source of energy for our devices. It is equipped with numerous power outlets, both DC and AC. There are **6 USB inputs**, including 2 USB-C ports, **3 DC 12 V inputs** and **2 AC 230 V sockets**. This makes it extremely versatile. It can serve as a power source not only for mobile phones, but also laptops, digital cameras and CPAP devices. In addition, the power station has a **51,000 mAh battery**, so it can be used for a very long time.

The AK-PS-01 power station is able to deliver **1,200 watts of continuous power**, so you can also power larger electronic devices such as a TV or refrigerator with it. Therefore, it is an ideal solution not only in the open air, but also at home during a blackout. What's more, the station is equipped with an **LCD display** that allows you to keep track of the battery status. In addition, there is an **LED light** on the side of the housing, which can serve as an emergency light source.